



WD4-BS20 is a ring scanner with Bluetooth 5.0 and compatible with mobile phones and tablets.



### LED indicator

LED off: off/sleep mode

Red LED on: charging

Green LED on: full battery

Red LED flashes slowly: battery less than 10%

Blue LED on: battery is more than 10% and Bluetooth connected

Blue LED flashes: battery is more than 10% and Bluetooth disconnected

*\*\* When connecting USB cable, battery related LED has the priority to show and when disconnecting USB cable, Bluetooth related LED has the priority to show.*

- 1 Long press on/off button for 3 seconds to power on
- 2 WD4-BS20 will auto sleep without operating for 1 minute in manual decoding mode
- 3 Long press on/off button for 8 seconds to force power off

Scan the Enter setup before barcode setting and scan the Exit setup after barcode setting.

### 1 Enter/Exit setup



Enter setup



Exit setup

### 2 Good read beep



On



Off

### 3 Good read vibration



On



Off

## 4 Bluetooth mode



@INTERF10

Bluetooth HID mode



@INTERF11

Bluetooth BLE mode

## 5 Clear Bluetooth pairing



@WLSCLP

Clear Bluetooth pairing

Clear Bluetooth pairing information  
before change to other host

## 6 Terminating character suffix



@TSUENA1

Enable terminating character suffix



@TSUSET0D

Set terminating character to CR  
(carriage return)

## 7 Factory defaults



@TSUSET0D0A

Enable terminating character to CRLF (0x0D, 0x0A)



@TSUENA0

Set terminating character to CR  
(carriage return)

## 7 Factory defaults



@FACDEF

Restore all factory defaults

## WD4-BS20

Name: WD4 Ring Scanner

Manufacturer: Newland EMEA

All technical information are subject to the actual  
performance, Newland reserve the right of final  
explanations.

Newland Europe BV

Rolweg 25

4104 AV Culemborg

The Netherlands

For more information, please visit

[www.newland-id.com](http://www.newland-id.com)